

CICS and IPCS

Andre Clark
Staff CICS L2 Support

Agenda

- Dump types
- Some basic IPCS commands
- CICS Verbexit DFHPDxxx
 - Common System Area (CSA)
 - Storage Manager (SM)
 - Transaction Manager (XM)
 - Dispatcher (DS)
 - Kernel (KE)
 - Loader domain (LD)
 - Program domain (PG)
 - Lock Manager (LM)
 - Enqueue domain (NQ)
 - Application domain (AP)
 - Task Summary (TK)
 - Trace (TR)

IPCS Primary Menu

```
----- IPCS PRIMARY OPTION MENU -----
OPTION  ==>

0  DEFAULTS  - Specify default dump and options
1  BROWSE    - Browse dump data set
2  ANALYSIS  - Analyze dump contents
3  UTILITY   - Perform utility functions
4  INVENTORY - Inventory of problem data
5  SUBMIT    - Submit problem analysis job to batch
6  COMMAND   - Enter subcommand, CLIST or REXX exec
T  TUTORIAL  - Learn how to use the IPCS dialog
X  EXIT      - Terminate using log and list defaults

*****
*  USERID   - USASSC1
*
*
*  TIME      - 16:46
*  PREFIX    - USASSC1
*  TERMINAL  - 3278
*  PF KEYS   - 24
*****
```

Enter END command to terminate IPCS dialog

```
F1=HELP    F2=SPLIT  F3=END    F4=RETURN  F5=RFIND  F6=MORE    F7=UP
F8=DOWN    F9=SWAP   F10=LEFT  F11=RIGHT  F12=CURSOR
```

IPCS Default Menu

----- IPCS Default Values -----
Command ==>

You may change any of the defaults listed below. The defaults shown before any changes are LOCAL. Change scope to GLOBAL to display global defaults.

Scope ==> BOTH (LOCAL, GLOBAL, or BOTH)

If you change the Source default, IPCS will display the current default Address Space for the new source and will ignore any data entered in the Address Space field.

Source ==> **DSNAME('USASSC1.SHAREFC.DUMP')**

Address Space ==> ASID(X'0044')

Message Routing ==> NOPRINT TERMINAL

Message Control ==> FLAG(WARNING) NOCONFIRM VERIFY

Display Content ==> MACHINE REMARK REQUEST NOSTORAGE SYMBOL

Press ENTER to update defaults.

Use the END command to exit without an update.

IPCS Primary Menu

```
----- IPCS PRIMARY OPTION MENU -----  
ION ==>  
  
0  DEFAULTS      - Specify default dump and options  
1  BROWSE        - Browse dump data set  
2  ANALYSIS      - Analyze dump contents  
3  UTILITY       - Perform utility functions  
4  INVENTORY     - Inventory of problem data  
5  SUBMIT        - Submit problem analysis job to batch  
6  COMMAND      - Enter subcommand, CLIST or REXX exec  
T  TUTORIAL      - Learn how to use the IPCS dialog  
X  EXIT          - Terminate using log and list defaults  
  
*****  
*  USERID      - USASSC1  
*  
*  
*  TIME        - 16:46  
*  PREFIX      - USASSC1  
*  TERMINAL    - 3278  
*  PF KEYS     - 24  
*****
```

Enter END command to terminate IPCS dialog

```
F1=HELP   F2=SPLIT   F3=END     F4=RETURN  F5=RFIND   F6=MORE    F7=UP  
F8=DOWN   F9=SWAP    F10=LEFT  F11=RIGHT  F12=CURSOR
```

IPCS Command Menu

----- IPCS Subcommand Entry -----
Enter a free-form IPCS subcommand or a CLIST or REXX exec invocation below:

====> **ST SYS**

----- IPCS Subcommands and Abbreviations -----

ADDUMP	DROPDUMP, DROPD	LISTDUMP, LDMP	RENUM, REN
ANALYZE	DROPMAP, DROPM	LISTMAP, LMAP	RUNCHAIN, RUNC
ARCHECK	DROPSYM, DROPS	LISTSYM, LSYM	SCAN
ASCBEXIT, ASCBX	EPTRACE	LISTUCB, LISTU	SELECT
ASMCHECK, ASMK	EQUATE, EQU, EQ	LITERAL	SETDEF, SETD
CBFORMAT, CBF	FIND, F	LPAMAP	STACK
CBSTAT	FINDMOD, FMOD	MERGE	STATUS, ST
CLOSE	FINDUCB, FINDU	NAME	SUMMARY, SUMM
COPYDDIR	GTFTRACE, GTF	NAMETOKN	SYSTRACE
COPYDUMP	INTEGER	NOTE, N	TCBEXIT, TCBX
COPYTRC	IPCS HELP, H	OPEN	VERBEXIT, VERBX
CTRACE	LIST, L	PROFILE, PROF	WHERE, W

Some useful IPCS commands

- **CBFORMAT (CBF)** – Displays a formatted control block.
 - **CBF RTCT** – Formats the Recovery Termination Control Table.
 - Can be used to see what address spaces are included in the dump.
 - **CBF address STR(control block name)** e.g. **ip cbf 12345678 str(rtm2wa)**
- **EQUATE (EQ)** – Assigns a name to the current address.
- **FIND (F)** – Locate data in a dump.
 - **F 'charstring' NOB** (NOB indicates No Break for uninterrupted searching).
 - **F x'datastring' NOB** - Locates a hexadecimal string.
- **LIST (L)** – Display storage at an address.
 - **L addr LEN(x'1000')** – List x'1000' bytes starting at the specified address.
 - **L addr+100** – List the specified address +x'100'.
 - **L SLIPTRAP** – List the slip trap for which a SLIP dump was taken.
 - **L addr INSTR** – Displays Assembler instructions at the specified address.

• e.g. **ip 123d00 l(x'20') i**
 LIST 023D00. ASD(X'0097') LENGTH(X'20') INSTRUCTION
 ASD(X'0097') ADDRESS(023D00.) KEY(00) ABSOLUTE(49FD00.)

00023D00 | BF6F C2F4 | ICM R6,X'F',X'2F4'(R12)

00023D04 | 9505 600A | CLI X'A'(R6),X'05'

00023D08 | 4770 B056 | BC X'7',X'56'(.R11)

Some useful IPCS commands (cont)

- **LISTTOD (LTOD)** - Convert TOD clock to corresponding timestamps.

- e.g. **ip ltod C6BC0E414486E884**

10/15/2016	23:58:44.955246	STCK	X'C6BC0E41 4486E884'
10/15/2016	23:58:44.955246	UTC	X'C6BC0E41 4486E884'
10/15/2016	17:58:44.955246	LOCAL	X'C6BBBDC9 E706E884'

- Top STCK is formatted GMT time without being adjusted for time zone or leap seconds.
- Middle UTC has been adjusted for leap seconds.
- Local time has been adjusted for both time zone and leap seconds.
- **HELP** - Provides a list of IPCS commands and subcommands.
 - **HELP** subcommand e.g. **ip help runchain**
- **LPAMAP** - Display LPA module summary.
- **OPCODE** - Converts a hex instruction to it's corresponding Assembler instruction.
- **RUNCHAIN (RUNC)** - Format a chain of control blocks.
 - e.g. **ip runc addr(12345678) len(x'20') link(x'10') chain(99) display verify**
 - ADDR - Address of first block in chain.
 - LEN - Length of block to be displayed.
 - LINK - Offset in each block for the next block on the chain.
 - CHAIN - Number of control blocks to chain; default is 999.

Commonly used IPCS commands (cont)

- **SELECT** – Displays address space/jobname information.
 - **ALL**
 - **ASID (x'...')** or **ASID (x'...',x'...')** for multiple address spaces.
- **STATUS (ST)** – Provides system status; includes dump title.
 - **STATUS SYSTEM (ST SYS)** – Includes time dump was taken.
 - **STATUS REGS (ST REGS)** – Formats PSW/registers when SLIP trap springs.
- **SUMMARY FORMAT (Summ Format)** – Formats TCBs and related information.
 - **SUMFOSUM ASID(...) TCB(...)** – Formats a summary of a TCB's RB structure
- **SYSTRACE** – Format MVS system trace table.
 - **TIME(LOCAL)**
 - **PERFDATA** – Help identify specific trace entries that are using CPU time
 - e.g. **systrace time(local) asid(x'101') tcb(x'9F8220')**
- **VERBEXIT (VERBX)** – User-supplied VERB exits – CICS, DB2, LE/370 etc.
 - **DFHPDxxx** (where 'xxx' is the CICS release e.g. 660, 670, 680, 690, 700, 710).
 - **VERBX MTRACE** – Formats the most recent console messages.
 - **VERBX LOGDATA** – Formats the most recent LOGREC entries.
- **WHERE (W)** – Identify an area of storage.
 - e.g. **Where 0E200200:**

```
ASID(X'0097') 0E200200. AREA(Subpool252Key00)+0200 IN EXTENDED PRIVATE
ASID(X'0097') 0E200200. DFHSIP+0200 IN EXTENDED PRIVATE
```

Status commands

- **Status (ST)**

- Displays the dump title:

Dump Title: CICS DUMP: SYSTEM=IYNXS CODE=XM0002 ID=64/0064

- The title tells you who requested the dump:
 - CICS, SLIP, console dump, or another product.
 - Dump title can give clues about the health of CICS or error information that will be available.

- **Status System (ST SYS)**

- Displays the time the dump was requested, and the difference between Local time and GMT:

TIME OF DAY CLOCK: C70F090C C054DA04 12/20/2016 23:57:24.279629 Local

TIME OF DAY CLOCK: C70F5984 1DD4DA04 12/21/2016 05:57:24.279629 GMT

Program Producing Dump: SVCDUMP

Program Requesting Dump: DFHKETCB

Incident token: P1 LSYS 12/21/2016 05:57:23.384554 GMT

What address spaces are included?

- **Cbf rtct**

- Displays the ASIDs that are included in the dump:

SDAS	SDF4	SDF5	
	----	----	----
001	<u>0144</u>	80	00
002	<u>016C</u>	80	00

- **Select all** formats all jobs and assigned address spaces.
- **Select asid(x'144',x'16C')** displays selected ASIDs and the associated jobnames:

ASID	JOBNAME	ASCBADDR	SELECTION CRITERIA
----	-----	-----	-----
0144	<u>CICSAOR</u>	00EE8B00	ASID
016C	<u>CICSTOR</u>	00F94880	ASID

- When multiple address spaces are dumped, can limit output to just one job with the job=parm:
 - **verbx dfhpd700 'ds=1,job=jobname'**

Browsing the dump

- Option 1 on the IPCS Menu Panel.
- Addresses that begin with an alphabetic character must be preceded by a 0 or followed by a period(.)
- Indirect addressing.
 - % - Displays storage at a selected 24 bit address
 - ? - Displays storage at a selected 31 bit address
 - ! - Displays storage at a selected 64 bit address

```
ASID(X'010B') ADDRESS(1BE02100.) STORAGE -----
1BE02100 ? 1BE02200 00000000 00000000 0004D948 | .\.....R. |
1BE02110 1C93D840 00000000 00000000 00000000 | .lQ ..... |
1BE02120 0000054C 00000000 00000000 80D0357C | ...<.....}.@ |
```

Entering the ? as above will display the storage at 1BE02200:

```
ASID(X'010B') ADDRESS(1BE02200.) STORAGE -----
1BE02200.:1BE0220F. LENGTH(X'10')--All bytes contain X'00'
1BE02210 0000054C 283452F0 0000008A 00000000 | ...<...0..... |
```

CICS Verbexit

- **Verbx dfhpdxxx** where 'xxx' is the CICS release:
 - 670 - CICS TS 4.2 (End of Service September 30 2018)
 - 680 - CICS TS 5.1
 - 690 - CICS TS 5.2
 - 700 - CICS TS 5.3
 - 710 - CICS TS 5.4
- When formatting information from a CICS domain or component, there are normally three levels of detail available:
 - 1 - Summary only
 - 2 - Full control block formatting
 - 3 - Both Summary and control blocks
- If the level number is omitted, formatting defaults to level 3 (both summary and control blocks) for components that have a summary, and level 2 for those that don't.

CICS Verbexit options

Keyword Functional area

AI = 0 2	Autoinstall Model Manager
AP = 0 1 2 3	Application Domain APS=<TASKID=nnnnn>
AU = 0 2	CICS affinities utility
BA = 0 1 2 3	Business application manager
BR = 0 1 2 3	3270 bridge
CC = 0 2	CICS catalog domain
CP = 0 2	Common Programming Interface
CQ = 0 1 2	Auto install model manager
CSA = 0 2	CICS Common System Area
DB2 = 0 1 2 3	The CICS DB2 interface
DD = 0 1 2 3	Directory Domain
DH = 0 1 2 3	Document handling domain
DLI = 0 2	CICS DL/I Interface
DM = 0 1 2 3	Domain Manager
DP = 0 1 2 3	Debug Profiles manager (630)
DS = 0 1 2 3	Dispatcher Domain
DU = 0 2	Dump Domain
EC = 0 1 2 3	Event Capture domain (660)
EJ = 0 1	Enterprise JAVA
EM = 0 1 2 3	Event manager domain for BTS
EP = 0 1 2 3	Event Processing domain (660)
FCP = 0 2	File Control Program
FT = 0 1 2 3	CICS WEB Interface
ICP = 0 2	Interval Control Program
IE = 0 1 2 3	IP ECI Domain
II = 0 1 2 3	IIOP
IND = 0 1 2 3	Page number indexes for output
IS = 0 1 2 3	IP Interconnectivity domain (650)
JCP = 0 2	Journal Control Program
KE = 0 1 2 3	CICS Kernel
LD = 0 1 2 3	Loader Domain
LG = 0 1 2 3	Logger Domain
LM = 0 1 2 3	Lock Manager domain
ME = 0 2	Message domain
ML = 0 1 2 3	Markup Language domain (660)
MN = 0 1 2 3	Monitoring domain
MQ = 0 1 2 3	CICS-MQ interface (650)

Keyword Functional area

MRO = 0 2	CICS Multi-Region Operation
NQ = 0 1 2 3	Enqueue Manager
OT = 0 1 2 3	Object Transaction Domain
PA = 0 2	Parameter manager domain
PCP = 0 2	Program Control Program
PCT = 0 2	Program Control Table
PG = 0 1 2 3	Program Manager Domain
PI = 0 1 2 3	Pipeline Domain (640)
PR = 0 2	Partner Resource management
PT = 0 1 2 3	Partner Domain
RD = 0 2	Resource definition manager
RL = 0 1 2 3	Resource Lifecycle domain (660)
RM = 0 2	Recovery Management
RS = 0 1 2 3	Region Status domain (660)
RX = 0 1 2 3	Recoverable EXCI domain
RZ = 0 1 2 3	Request Streams
SH = 0 1	Scheduler services domain for BTS
SJ = 0 1 2 3	JVM Domain
SM = 0 1 2 3	Storage Manager domain
SO = 0 1 2 3	Sockets domain
SSA = 0 2	Static Storage Areas
ST = 0 1 2 3	Statistics domain
SZ = 0 1	Front End Programming Interface
TCP = 0 1 2 3	Terminal Control Program
TDP = 0 1 2 3	Transient Data Program
TI = 0 1 2 3	Timer domain
TMP = 0 2	Table Manager Program
TR = 0 1 2 3	Trace domain TRS=<trace selection parameters>
TS = 0 1 2 3	Temporary Storage Program
UEH = 0 2	User Exit Handler
US = 0 1 2 3	User Domain
WB = 0 1 2	The web interface
W2 = 0 1 2 3	Web 2.0 domain (660)
XM = 0 1 2 3	The transaction manager
XRF = 0 2	The extended recovery facility
XS = 0 1	Security Domain

1 - Summary only

2 - Full control block formatting

3 - Both 1 and 2. If you omit the level number, it defaults to level 3 for components that have a summary, and level 2 for those that do not.

IPCS Subcommand Menu

----- IPCS Subcommand Entry

Enter a free-form IPCS subcommand or a CLIST or REXX exec invocation below:

==> **verbx dfhpd700 'ke=1'**

----- IPCS Subcommands and Abbreviations

ADDUMP	DROPDUMP, DROPD	LISTDUMP, LDMP	RENUM, REN
ANALYZE	DROPMAP, DROPM	LISTMAP, LMAP	RUNCHAIN , RUNC
ARCHECK	DROPSYM, DROPS	LISTSYM, LSYM	SCAN
ASCBEXIT, ASCBX	EPTRACE	LISTUCB, LISTU	SELECT
ASMCHECK, ASMK	EQUATE , EQU , EQ	LITERAL	SETDEF, SETD
CBFORMAT , CBF	FIND , F	LPAMAP	STACK
CBSTAT	FINDMOD, FMOD	MERGE	STATUS , ST
CLOSE	FINDUCB, FINDU	NAME	SUMMARY , SUMM
COPYDDIR	GTFTRACE, GTF	NAMETOKN	SYSTRACE
COPYDUMP	INTEGER	NOTE, N	TCBEXIT, TCBX
COPYTRC	IPCS HELP , H	OPEN	VERBEXIT , VERBX
CTRACE	LIST , L	PROFILE, PROF	WHERE , W

CSA Time of Day clock (CSA)

- The CICS CSA has a timestamp that is updated each time a task is dispatched on the QR TCB.
 - It is also updated when an application program issues an EXEC CICS ASKTIME request.
- This timestamp is in the form HHMMSSSTF Local time, and can be found in the **CSA +x'50'**.
- If CICS is hung, compare the CSA TOD clock to the time of the dump to see when a task was last dispatched on the QR TCB.

• Verby dfhpd700 'csa'

CSA 0004E200 Common System Area

0000	00000	200	00050020	0004E3A0	86F7EA74	8AE7013C	8004E200	1C276598	1C278158
0020	8B1DDDB28	8B1DD6B8	1C2784E0	1C861CF0	0004D948	7F228020	0B1DEB28	1C88B7F0	
0040	00052020	1BE08700	2094125C	009A7000	<u>2231233F</u>	1CC19108	00000100	00000000	

Storage Manager (SM)

- Storage manager summaries show whether CICS is short-on-storage (SOS), above/below the line, above bar.
 - Also shows whether Storage Protection, Reentrant Program Protection, and Transaction Isolation are active.
- **Verbx dfhpd700 'sm=1'**

```
===SM: STORAGE MANAGER DOMAIN - SUMMARY
```

SM Domain status:	INITIALISED
-------------------	-------------

Storage recovery:	YES
-------------------	-----

Storage protection requested:	YES
-------------------------------	-----

Storage protection active:	<u>YES</u>
-----------------------------------	-------------------

Reentrant program option:	<u>PROTECT</u>
----------------------------------	-----------------------

Transaction isolation requested:	NO
----------------------------------	----

Transaction isolation active:	<u>NO</u>
--------------------------------------	------------------

Current DSA limit:	5120K
--------------------	-------

Current DSA total:	5120K
--------------------	-------

Transaction Manager (XM)

- Transaction manager summaries show:
 - Whether CICS is at MAXTASK:
 - Whether tasks are held for TRANCLASS reasons.
 - Tasks that have been attached but queued for MAXTASK or TCLASS reasons will not be in the CICS Dispatcher or Kernel summaries.
- Transaction manager summaries and control blocks can also be used to determine what time a task was attached.
- **Verbx dfhpd700 'xm=1'**

==XM: GLOBAL STATE SUMMARY

XM domain status:	Initialised
Maximum user tasks (MXT):	90

System currently at MXT:	<u>Yes</u>
---------------------------------	-------------------

XXMATT user exit currently:	Inactive
-----------------------------	----------

XM state lock currently held:	No
-------------------------------	----

XM trandef state lock currently held:	No
---------------------------------------	----

System attaches delayed for SOS:	No
----------------------------------	----

Transaction Summary (XM)

- **Verbx dfhpd700 'xm=1'**

==XM: TRANSACTION SUMMARY

Tran id	Tran num	TxnAddr TxdAddr	Start code	Sys Tran	Status	DS token	Facility type	Facility token	AP token
CSOL	00003	0E609300 0F659BE0	C	Yes	ACT	00040003	None		0E6D6800 00000000
CEPM	00005	0E609700 0F60D140	C	<u>Yes</u>	ACT	000A0003	None		0E6D7100 00000000
...									
BIGD	46840	1BC291B8 1BA21920	T	<u>No</u>	ACT	059020F9	Terminal	1BFA2220	1AF40080 00000000
BIGD	53732	1BC29340 1BA21920	T	No	<u>TCLASS</u> DFHTCL01	00000000	None		00000000 00000000
CWXN	90669	24CA4500 1912B510	C	No	<u>MXT</u>	00000000	None		00000000 00000000
CWXN	90670	24CA4700 1912B510	C	No	<u>MXT</u>	00000000	None		00000000 00000000

MXT Summary (XM)

- **Verbx dfhpd700 'xm=1'**
- MXT and TCLASS Summaries are at the end of the formatted summaries.
 - Max to the bottom of the formatted output by entering m followed by PF8.

```
==XM: MXT SUMMARY
```

```
Maximum user tasks (MXT): 90
```

```
System currently at MXT: Yes
```

```
Current active user tasks: 90
```

```
Current queued user tasks: 32805
```

```
* Peak active user tasks: 90
```

```
* Peak queued user tasks: 32835
```

```
* Times at MXT limit: 1
```

TCLASS Summary (XM)

- Page backwards from the MXT Summary to see the TCLASS summary:

==XM: TCLASS SUMMARY

Tclass	Max	Purge	Current	Current	Total	Queuing	Queuing	Queuing
Time Name	Active	Threshld	Active	Queued	Attaches	TranNum	Transid	Start
-----	-----	-----	-----	-----	-----	-----	-----	
DFHTCL01	20	0	20	3707	66475	67732	BIGE	
18:37:01.06						67734	BIGE	
18:37:01.13						67752	BIGE	
18:37:02.23						...		
						90352	BIGE	
18:53:14.26						90356	BIGE	
18:53:14.52						90358	BIGE	
18:53:14.65						90368	BIGE	

Task Attach Time (XM)

- Verbx dfhpd700 'xm=3'

==XM: TRANSACTION SUMMARY

Tran id	Tran num	TxnAddr TxdAddr	Start code	Sys Tran	Status	DS token	Facility type	Facility token	AP token
CSOL	00003	<u>1B709300</u> 1CE97360	C	Yes	ACT	00900003	None		1C203800 00000000

- FIND on the TXN address. Task attach time is in the **TXN +x'50'**:

TXN 1B709300 Transaction

0020	00000000	00000000	00000000	00000000	00000000	00000000	00000000	1B709300	0000003C
0040	1B709700	1B704034	C2E2D6D3	08000000	<u>C56197A6</u>	<u>49D40706</u>	00000000	00000000	00000000

- IP LTOD C56197A649D40706
- Task was attached at 04:25:48.113216 Local time.

01/13/2017	10:25:48.113216	STCK	X'C56197A6 49D40706'
01/13/2017	10:25:48.113216	UTC	X'C56197A6 49D40706'
01/13/2017	04:25:48.113216	LOCAL	X'C561472E EC540706'

Dispatcher (DS)

- Dispatcher summary displays:
 - Tasks currently in the system.
 - Each task's current status - running, suspended, dispatchable , etc.
 - What resources tasks are waiting for.
 - The resource names are described in the CICS InfoCenter (or CICS Problem Determination Guide).
 - What time a task suspended, and whether there is a time-out due.
- Dispatcher summaries and control blocks can be used to determine:
 - How long tasks have been running on their respective TCBs.
 - How long tasks have been dispatchable, waiting for a turn to run on a particular TCB.
- Note: Times in the Dispatcher Summary have not been adjusted for time zone or leap seconds.

Dispatcher Task Summary (DS)

• Verbx dfhpd700 'ds=1'

==DS: TASKS SUMMARY

KEY FOR SUMMARY

T = TYPE OF TASK
S = STATE OF TASK
F = PURGEABILITY FLAG
P = PURGE STATUS
TT = TIMEOUT TYPE
W = WAIT/SUSPEND TYPE
DTA= DISPATCHER TASK AREA

S=SYSTEM N=NON-SYSTEM
D=DISPATCHABLE S=SUSPENDED R=RUNNING A=RUNNING ABTERM YES J=RUNNING IN JVM E=RESUMED EARLY
P=PURGEABLE N=NOT PURGEABLE
N=NO PURGE X=PURGED P=PURGE PENDING A=ABTERM PENDING
IN=INTERVAL DD=DEADLOCK DELAYED DI=DEADLOCK IMMEDIATE
M=WAIT_MVS S=SUSPEND C=WAIT_OLDC W=WAIT_OLDW

AD = ATTACHING DOMAIN

M = TASK MODE

Shows whether a task is running, suspended, dispatchable etc

Task #

DS_TOKEN	KE_TASK	T	S	F	P	TT	RESOURCE TYPE	RESOURCE NAME	W	TIME OF SUSPEND	TIMEOUT DUE	DTA (DSTSK)	AD	ATTACHER TOKEN	M	SUSPAREA	XM_TXN_TOKEN
00000001	1AAADA98	S	S	N	N	-	ENF	NOTIFY	M	06:16:26.706	-	1B6A3080	DM	1B772C00	R	1B772C18	
00060003	1AACBA98	S	R									1B6A3500	AP	80051300	CQ		
000A0003	1CECE100	S	S	N	N	-	EPECQEMT	EPSUSPND	M	06:18:17.081	-	1B6A3800	XM	1B709700	EP	1CEC5050	1B709700000005C
000E0003	1B790700	S	S	N	N	-	KCCOMPAT	SINGLE	W	06:19:28.426	-	1B6A3B00	XM	1B70AB00	QR	000418B8	1B70AB00000036C
00820003	1B68D530	S	S	N	N	IN	LGHARTBT	LG_MGRST	S	21:20:37.145	21:20:47.14	1B6C8200		D3C7C8C2	QR	1B6C8200	
00840005	1CFDB100	S	S	N	N	-	CSNC	MROQUEUE	M	21:20:41.828	-	1B6C8380	XM	1B709100	QR	1B79D03C	1B709100000025C
00900003	1B6EDA98	S	S	N	N	-	SODOMAIN	SO_NOWORK	M	21:05:34.378	-	1B6C8C80	XM	1B709300	SL	1B777730	1B709300000003C
00920003	1CF75700	S	S	N	N	-	TCP_NORM	DFHZDSP	W	21:20:39.590	-	1B6C8E00	XM	1B70A100	QR	00056FD0	1B70A100000010C
...																	
0B0209ED	16D9B100	N	S	P	N	-	IRLINK	AOR2S006	M	13:08:56.110	-	20B4B200	XM	18CF2100	QR	7F46B200	18CF2100045441C
07046CFB	1E584900	N	R									1D5F4380	XM	1EDA6100	QR		1EDA6100043738C
07061887	1E4BA100	N	S	N	N	-	LMQUEUE		S	20:00:30.503		1D5F4500	XM	2170DD00	QR	1D395200	2170DD00044047C
070C338D	1E48E100	N	D									1D5F4980	XM	2170DB00	L8		2170DB00044046C
07040001	2BDC1480	N	S	P	N	-	ENQUEUE	FCDSRECD	S	20:01:11.363	-	2B0E2380	XM	2E40C030	QR	2B0E2380	2E40C030043203C
0782000B	1E5DE900	N	S	N	N	-	EKCWAIT	STNGLE	W	05:08:26.187	-	1D5F6200	XM	1D609B00	QR	00006058	1D609B00000076C

Shows what TCB a task is running on, suspended on, or waiting to run on

What time did a task become 'Running' or Dispatchable?

- Dispatcher Task Summary shows the time a task was suspended, but not what time a task became 'Running' or 'Dispatchable'.
 - Tasks that are ready to run but the dispatcher hasn't dispatched them yet are 'Dispatchable'.
- Dispatcher Task Summary includes the address of the Dispatcher Task Area (DTA) control block.
 - DTA has two clock fields at +x'50' and +x'58'.
- When a task is 'Dispatchable', the **DTA +X'50'** contains the time the task became dispatchable.
 - For a suspended task, DTA +X'50' is also the time the task was suspended.
- For a running task, **DTA +X'58'** is within .1 second of the time the task became 'running' (i.e. was dispatched).

What time did a task become Running ?

- **Verbx dfhpd700 'ds=3'**

DS_TOKEN	KE_TASK	T	S	F	P	TT	RESOURCE TYPE	RESOURCE NAME	W	TIME OF SUSPEND	TIMEOUT DUE	DTA (DSTSK)	AD	ATTACHER TOKEN	M	SUSPAREA	XM_TXN_TOKEN
...																	
07046CFB	1E584900	N	R									1D5F4380	XM	1EDA6100	QR		1EDA6100043738C
07065887	1E4BA100	N	S	N	N	-		LMQUEUE	S	20:00:30.503	-	1D5F4500	XM	2170DD00	QR	1D395200	2170DD00044047C
070C338D	1E48E100	N	D									1D5F4980	XM	2170DB00	QR		2170DB00044046C
020A0003	20FCE100	S	D									30288800	XM	20FCC900	QR		20FCC900043202C
020C0001	20FCE500	S	D									30288980	XM	20FCCB00	QR		20FCCB00043276C
020E0001	20FCE900	S	D									30288B00	XM	20FCCD00	QR		20FCCD00043373C
02100003	20FD2100	S	D									30288C80	XM	20FCC500	QR		20FCC500043444C
0A9202AD	16E23500	N	S	P	N	-	IRLINK	AOR2S003	M	13:08:25.177	-	20B4AE00	XM	18EF1900	QR	7F46B320	18EF1900044796C

- **FIND on the DTA address to get to the formatted DTA control block. Check the DTA +x'58':**

DTA 1D5F4380 DISPATCHER TASK AREA																	
0000	FFFFFFFF	07046CFB	40404040	40404040	D3D4D8E4	C5E4C540	40404040	40404040	*	%.						LMQUEUE	*
0020	1D5F4380	00040000	FE000000	1D5AD080	FFFFFFFF	00000000	FFFFFFFF	FFFFFFFF	*	^.....!}							*
0040	00000000	02FF0000	00000000	00000000	00000000	00000000	00000000	00000000	*	J..FF....						00FF.. .Sd*	

- **Ip Itod C6C676564F3AE284 will convert the time to show that the running task became 'Running' within .1 sec of:**

10/24/2016	06:37:39.073966	STCK	X'C6C67656 4F3AE284'
10/24/2016	06:37:39.073966	UTC	X'C6C67656 4F3AE284'
10/24/2016	01:37:39.073966	LOCAL	X'C6C63348 2BFAE284'

What time did a task become Dispatchable ?

- **Verbx dfhpd700 'ds=3'**

DS_TOKEN	KE_TASK	T	S	F	P	TT	RESOURCE TYPE	RESOURCE NAME	W	TIME OF SUSPEND	TIMEOUT DUE	DTA (DSTSK)	AD	ATTACHER TOKEN	M	SUSPAREA	XM_TXN_TOKEN
...																	
07046CFB	1E584900	N	R									1D5F4380	XM	1EDA6100	QR		1EDA6100043738C
07065887	1E4BA100	N	S	N	N	-		LMQUEUE	S	20:00:30.503	-	1D5F4500	XM	2170DD00	QR	1D395200	2170DD00044047C
070C338D	1E48E100	N	D									1D5F4980	XM	2170DB00	QR		2170DB00044046C
020A0003	20FCE100	S	D									30288800	XM	20FCC900	QR		20FCC900043202C
020C0001	20FCE500	S	D									30288980	XM	20FCCB00	QR		20FCCB00043276C
020E0001	20FCE900	S	D									30288B00	XM	20FCCD00	QR		20FCCD00043373C
02100003	20FD2100	S	D									30288C80	XM	20FCC500	QR		20FCC500043444C
0A9202AD	16E23500	N	S	P	N	-	IRLINK	AOR2S003	M	13:08:25.177	-	20B4AE00	XM	18EF1900	QR	7F46B320	18EF1900044796C

- **FIND on the DTA address to get to the formatted DTA control block. Check the DTA +x'50':**

DTA 1D5F4980 DISPATCHER TASK AREA																	
0000	FFFFFFFF	070C338D	C4E2E3E2	D2C4C5C6	070C338D	E3E9F140	40404040	40404040	*	DSTSKDEF....TZ1	*						
0020	1D5F4980	00010000	FE000000	1D5FF680	1D5F3200	00000000	FFFFFFFF	FFFFFFFF	*	^.....^6..^.....*							
0040	00000000	03FF0000	3938922F	9F7B81FB	C6C6DEF 925B7E05	C6C5C0CF	5E82D285		*	k..#a.FF_.k\$=.FE{.;bKe*							

- **IP LTOD C6C66DEF925B7E05 will convert the time to show that the task became 'Dispatchable' at:**

10/24/2016	06:00:03.861943	STCK	X'C6C66DEF 925B7E05'
10/24/2016	06:00:03.861943	UTC	X'C6C66DEF 925B7E05'
10/24/2016	01:00:03.861943	LOCAL	X'C6C62AE1 6F1B7E05'

Kernel (KE)

- **Verbx dfhpd700 'ke=1'**
- Task Summary
 - Includes all the tasks currently in the system.
 - Also includes a default task for each MVS TCB managed by the Kernel.
 - Shows tasks that are *****Running**** if the task is currently dispatched on a TCB.
 - Shows tasks flagged with an error (when any kernel stack for the task has been flagged with an error).
- Kernel Error Data (if applicable)
- Kernel Stacks
- Kernel Error Table Summary
 - Formats the 50 most recent errors in CICS.

Kernel Task Summary (KE)

• Verbx dfhpd700 'ke=1'

===KE: Kernel Domain KE_TASK Summary

KE_NUM	KE_TASK	STATUS	TCA_ADDR	TRAN_#	TRANSID	DS_TASK	KE_KTCB	ERROR
0001	0E38FA98	KTCB Step	00000000			00000000	0E3D3FE0	
0002	0E38F530	<u>KTCB QR</u>	00000000			0E603100	<u>0E3D6FF8</u>	
0003	0E39EA98	KTCB R0	00000000			0E603200	0E3D5FF0	
0004	0E39E530	KTCB F0	00000000			0E603300	0E3D4FE8	
0005	0E3ADA98	Not Running	00000000			0E582080	0E3D5FF0	
0006	0E3AD530	Not Running	0E6DC100	00040	CSNE	0E582200	0E3D6FF8	
0007	0E3BCA98	KTCB SL	00000000			0E603500	0E5BEFF8	
0008	0E3CBA98	***Running**	00000000			0E582680	0E58CFF8	
0009	0E3CB530	KTCB EP	00000000			0E603700	1220EFF8	
000A	0E3CA530	Not Running	00000000			0E582800	0E58CFF8	
000B	0E3C9530	Not Running	00000000			0E582900	0E58CFF8	
000C	0E3C8530	Not Running	00000000			0E582A00	0E58CFF8	
000D	0E3C7530	Not Running	00000000			0E582B00	0E58CFF8	
000E	0E3C6530	Not Running	00000000			0E582C00	0E58CFF8	
000F	0E3C5530	Not Running	00000000			0E582D00	0E58CFF8	
0010	0E3C4530	Not Running	00000000			0E582E00	0E58CFF8	
0011	0E3C3530	Not Running	00000000			0E582F00	0E58CFF8	
0012	0E3C2530	Not Running	00000000			0E583000	0E58CFF8	
0013	0E3C1530	Not Running	00000000			0E583100	0E58CFF8	
0014	0E3C0530	Not Running	00000000			0E583200	0E58CFF8	
0015	0E3BF530	Not Running	00000000			0E583300	0E58CFF8	
0016	0E3BE530	Not Running	00000000			0E583400	0E58CFF8	
0017	0E3BD530	Not Running	00000000			0E583500	0E58CFF8	
0018	0E3BC530	Not Running	00000000			0E583600	0E58CFF8	
0019	0E3BB530	Not Running	00000000			0E583700	0E58CFF8	
001A	0E3BA530	Not Running	00000000			0E583800	0E58CFF8	
001B	0E3B9530	Not Running	00000000			0E583900	0E58CFF8	
001C	0E3B8530	Not Running	00000000			0E583A00	0E58CFF8	
001D	0E3B7530	Not Running	00000000			0E583B00	0E58CFF8	
001E	0E3B6530	Not Running	00000000			0E583C00	0E58CFF8	
001F	0E3B5530	Not Running	00000000			0E583D00	0E58CFF8	
0020	0E3B4530	Not Running	00000000			0E583E00	0E58CFF8	
0021	0E3B3530	Not Running	00000000			0E583F00	0E58CFF8	
0022	0E3B2530	Not Running	00000000			0E584000	0E58CFF8	
0023	0E3B1530	Not Running	00000000			0E584100	0E58CFF8	
0024	0E3B0530	Not Running	00000000			0E584200	0E58CFF8	
0025	0E3AF530	Not Running	00000000			0E584300	0E58CFF8	
0026	0E3AE530	Not Running	00000000			0E584400	0E58CFF8	
0027	0E3AD530	Not Running	00000000			0E584500	0E58CFF8	
0028	0E3AC530	Not Running	00000000			0E584600	0E58CFF8	
0029	0E3AB530	Not Running	00000000			0E584700	0E58CFF8	
002A	12274A98	KTCB CQ	00000000			0E603400	0E58CFF8	
002B	0E3AA530	Not Running	00000000			0E584800	0E58CFF8	
002C	0E3A9530	Not Running	00000000			0E584900	0E58CFF8	
002D	0E3A8530	Not Running	00000000			0E584A00	0E58CFF8	
002E	0E3A7530	Not Running	00000000			0E584B00	0E58CFF8	
002F	0E3A6530	Not Running	00000000			0E584C00	0E58CFF8	
0030	0E3A5530	Not Running	00000000			0E584D00	0E58CFF8	
0031	0E3A4530	Not Running	00000000			0E584E00	0E58CFF8	
0032	0E3A3530	Not Running	00000000			0E584F00	0E58CFF8	
0033	0E3A2530	Not Running	00000000			0E585000	0E58CFF8	
0034	0E3A1530	Not Running	00000000			0E585100	0E58CFF8	
0035	0E3A0530	Not Running	00000000			0E585200	0E58CFF8	
0036	0E39F530	Not Running	00000000			0E585300	0E58CFF8	
0037	0E39E530	Not Running	00000000			0E585400	0E58CFF8	
0038	0E39D530	Not Running	00000000			0E585500	0E58CFF8	
0039	0E39C530	Not Running	00000000			0E585600	0E58CFF8	
003A	0E39B530	Not Running	00000000			0E585700	0E58CFF8	
003B	0E39A530	Not Running	00000000			0E585800	0E58CFF8	
003C	0E399530	Not Running	00000000			0E585900	0E58CFF8	
003D	0E398530	Not Running	00000000			0E585A00	0E58CFF8	
003E	0E397530	Not Running	00000000			0E585B00	0E58CFF8	
003F	0E396530	Not Running	00000000			0E585C00	0E58CFF8	
0040	0E395530	Not Running	00000000			0E585D00	0E58CFF8	
0041	0E394530	Not Running	00000000			0E585E00	0E58CFF8	
0042	0E393530	Not Running	00000000			0E585F00	0E58CFF8	
0043	0E392530	Not Running	00000000			0E586000	0E58CFF8	
0044	0E391530	Not Running	00000000			0E586100	0E58CFF8	
0045	0E390530	Not Running	00000000			0E586200	0E58CFF8	
0046	0E38F530	Not Running	00000000			0E586300	0E58CFF8	
0047	0E38E530	Not Running	00000000			0E586400	0E58CFF8	
0048	0E38D530	Not Running	00000000			0E586500	0E58CFF8	
0049	0E38C530	Not Running	00000000			0E586600	0E58CFF8	
004A	0E38B530	Not Running	00000000			0E586700	0E58CFF8	
004B	0E38A530	Not Running	00000000			0E586800	0E58CFF8	
004C	0E389530	Not Running	00000000			0E586900	0E58CFF8	
004D	0E388530	Not Running	00000000			0E586A00	0E58CFF8	
004E	0E387530	Not Running	00000000			0E586B00	0E58CFF8	
004F	0E386530	Not Running	00000000			0E586C00	0E58CFF8	
0050	0E385530	Not Running	00000000			0E586D00	0E58CFF8	
0051	0E384530	Not Running	00000000			0E586E00	0E58CFF8	
0052	0E383530	Not Running	00000000			0E586F00	0E58CFF8	
0053	0E382530	Not Running	00000000			0E587000	0E58CFF8	
0054	0E381530	Not Running	00000000			0E587100	0E58CFF8	
0055	0E380530	Not Running	00000000			0E587200	0E58CFF8	
0056	0E37F530	Not Running	00000000			0E587300	0E58CFF8	
0057	0E37E530	Not Running	00000000			0E587400	0E58CFF8	
0058	0E37D530	Not Running	00000000			0E587500	0E58CFF8	
0059	0E37C530	Not Running	00000000			0E587600	0E58CFF8	
005A	0E37B530	Not Running	00000000			0E587700	0E58CFF8	
005B	0E37A530	Not Running	00000000			0E587800	0E58CFF8	
005C	0E379530	Not Running	00000000			0E587900	0E58CFF8	
005D	0E378530	Not Running	00000000			0E587A00	0E58CFF8	
005E	0E377530	Not Running	00000000			0E587B00	0E58CFF8	
005F	0E376530	Not Running	00000000			0E587C00	0E58CFF8	
0060	0E375530	Not Running	00000000			0E587D00	0E58CFF8	
0061	0E374530	Not Running	00000000			0E587E00	0E58CFF8	
0062	0E373530	Not Running	00000000			0E587F00	0E58CFF8	
0063	0E372530	Not Running	00000000			0E588000	0E58CFF8	
0064	0E371530	Not Running	00000000			0E588100	0E58CFF8	
0065	0E370530	Not Running	00000000			0E588200	0E58CFF8	
0066	0E36F530	Not Running	00000000			0E588300	0E58CFF8	
0067	0E36E530	Not Running	00000000			0E588400	0E58CFF8	
0068	0E36D530	Not Running	00000000			0E588500	0E58CFF8	
0069	0E36C530	Not Running	00000000			0E588600	0E58CFF8	
006A	0E36B530	Not Running	00000000			0E588700	0E58CFF8	
006B	0E36A530	Not Running	00000000			0E588800	0E58CFF8	
006C	0E369530	Not Running	00000000			0E588900	0E58CFF8	
006D	0E368530	Not Running	00000000			0E588A00	0E58CFF8	
006E	0E367530	Not Running	00000000			0E588B00	0E58CFF8	
006F	0E366530	Not Running	00000000			0E588C00	0E58CFF8	
0070	0E365530	Not Running	00000000			0E588D00	0E58CFF8	
0071	0E364530	Not Running	00000000			0E588E00	0E58CFF8	
0072	0E363530	Not Running	00000000			0E588F00	0E58CFF8	
0073	0E362530	Not Running	00000000			0E589000	0E58CFF8	
0074	0E361530	Not Running	00000000			0E589100	0E58CFF8	
0075	0E360530	Not Running	00000000			0E589200	0E58CFF8	
0076	0E35F530	Not Running	00000000			0E589300	0E58CFF8	
0077	0E35E530	Not Running	00000000			0E589400	0E58CFF8	
0078	0E35D530	Not Running	00000000			0E589500	0E58CFF8	
0079	0E35C530	Not Running	00000000			0E589600	0E58CFF8	
007A	0E35B530	Not Running	00000000			0E589700	0E58CFF8	
007B	0E35A530	Not Running	00000000			0E589800	0E58CFF8	
007C	0E359530	Not Running	00000000			0E589900	0E58CFF8	
007D	0E358530	Not Running	00000000			0E589A00	0E58CFF8	
007E	0E357530	Not Running	00000000			0E589B00	0E58CFF8	
007F	0E356530	Not Running	00000000			0E589C00	0E58CFF8	
0080	0E355530	Not Running	00000000			0E589D00	0E58CFF8	
0081	0E354530	Not Running	00000000			0E589E00	0E58CFF8	
0082	0E353530	Not Running	00000000			0E589F00	0E58CFF8	
0083	0E352530	Not Running	00000000			0E58A000	0E58CFF8	
0084	0E351530	Not Running	00000000			0E58A100	0E58CFF8	
0085	0E350530	Not Running	00000000			0E58A200	0E58CFF8	
0086	0E34F530	Not Running	00000000			0E58A300	0E58CFF8	
0087	0E34E530	Not Running	00000000			0E58A400	0E58CFF8	
0088	0E34D530	Not Running	00000000			0E58A500	0E58CFF8	
0089	0E34C530	Not Running	00000000			0E58A600	0E58CFF8	
008A	0E34B530	Not Running	00000000			0E58A700	0E58CFF8	
008B	0E34A530	Not Running	00000000			0E58A800	0E58CFF8	
008C	0E349530	Not Running	00000000			0E58A900	0E58CFF8	
008D	0E348530	Not Running	00000000			0E58AA00	0E58CFF8	
008E	0E347530	Not Running	00000000			0E58AB00	0E58CFF8	
008F	0E346530	Not Running	00000000			0E58AC00	0E58	

Kernel Error Table Summary (KE)

- **Verbx dfhpd700 'ke=1'**

- Max to the bottom to see the Kernel Error Table summary.

==KE: KE Domain Error Table Summary

ERR_NUM =====	ERR_TIME =====	KE_NUM =====	ERROR TYPE =====	ERR_CODE =====	MODULE =====	OFFSET =====
00000001	10:56:35	0059	TRAN ABEND PERCOLATE	---/AFCY	DFHPCP	000005E8
00000002	10:56:35	0059	TRAN ABEND PERCOLATE	---/AFCY	DFHEIFC	00001298
00000003	10:56:35	0059	TRAN ABEND PERCOLATE	---/AFCY	DFHEIP	000008AC
00000004	11:32:40	0010	PROGRAM CHECK	0C1/AKEA	UNKNOWN	UNKNOWN
00000005	11:32:40	0010	TRAN ABEND PERCOLATE	---/ASRA	DFHSR1	00000598
00000006	11:41:34	0024	TRAN ABEND PERCOLATE	---/ATNI	DFHPCP	000005E8
00000007	11:41:34	0024	TRAN ABEND PERCOLATE	---/ATNI	DFHEIP	000024E8
00000008	11:41:34	0024	TRAN ABEND PERCOLATE	---/ATNI	DFHEPC	00000246
00000009	11:42:58	0010	PROGRAM CHECK	0C4/AKEA	UNKNOWN	UNKNOWN

- Kernel Error Table holds a maximum of the 50 most recent errors.
- ERR_CODE is the system abend code, if any, followed by the user abend code. (CICS abend codes begin with the letter 'A').
- Note the KE_NUM to identify errors associated with a particular kernel task.
 - May need to check task attach times to determine if errors associated with a kernel task are for the same task or different tasks.

Kernel Error Data (KERRD)

- **Verbx dfhpd700 'ke=1'**
- If the dump is taken for an error, Kernel Error Data will be formatted with the summary information.
 - If not, the most recent 50 errors can be found with:
 - **verbx dfhpd700 'ke=2'**
 - Find the error using the ERR_NUM identified in the Error Table Summary. e.g. **FIND 'number: 00000009'**
 - Note: 2 spaces between the colon and the error number.
- The dump formatter provides the raw KERRD control block which contains PSW, registers, and error information.
- The dump formatter also formats key areas:
 - PSW and registers, together with storage in the vicinity of the PSW and register addresses.
 - The module in control at time of error, from a CICS perspective.
 - If the error did not occur in the controlling program, the offset shown will be negative. i.e. FFFFFFFF
 - The execution key and space (Basespace or Subspace if Transaction Isolation is active).

Kernel Error Data (KERRD)

- There are two sets of PSW and Registers, CICS and MVS.
- These two save areas are different only when CICS has issued an SVC (service request), and an abend or program check occurs during execution of the code processing the SVC.
 - CICS PSW and registers will reflect the code that issued the SVC.
 - MVS PSW and registers will reflect the actual program check or abend.
 - MVS PSW and registers will only be formatted if they are different than the CICS PSW and registers.
 - The exception is when CICS has detected a runaway (looping) task. CICS issues an abend 999 to terminate the task:
 - CICS PSW and registers will point within the looping module.
 - MVS PSW and registers will point within Kernel module DFHKETIX after the abend SVC.
- BEAR – Breaking Event Address Register, is also formatted.
 - BEAR contains the address of the last branch instruction taken prior to a program check or abend. (Useful for wild branch detection).
 - Formatted as **Branch Event Address**.

Example Kernel Error Data (KERRD)

=KE: Error Number: 00000009
KERRD 1A3D69D0 KERNEL ERROR DATA

```

0000 F0C3F461 C1D2C5C1 018400C4 0000FFFF C4C6C8D9 D4C4D440 18D61FA8 193D0800 *0C4/AKEA.d.D..DFHRMDM .0.y...*
0020 0005F080 1A3D6700 00000001 00000010 078D0000 B92F8A7A 00040010 3D711000 *..0.....:.....*
0040 B92F8A7A 80800000 00000000 18E1EF30 00000000 1A3E5468 00000000 00007000 *.....:.....*
0060 00000000 98D61FA8 00000000 00076734 00000000 98CF7E20 00000000 388E2400 *....q0.y.....q.=.....*
0080 00000000 B92F87F0 00000000 04418558 00000000 B92F97F0 00000000 1A3E5468 *.....g0....e.....p0.....*
00A0 00000000 0000B8F0 00000000 0005F080 00000000 1A3E4F90 00000000 98D64AA2 *.....0....0.....|.....q0qs*
00C0 00000000 B92F8940 983315D6 00000000 00000000 00000000 00000000 *.....i q..0.....*
00E0 00000000 00000000 00000000 00000000 00000000 00000000 00000000 *.....:.....*
0100 00000000 00000000 078D0000 B92F8A7A 00040010 3D711000 B92F8A7A 80800000 *.....:.....*
0120 00000000 18E1EF30 00000000 1A3E5468 00000000 00007000 00000000 98D61FA8 *.....:.....q0.y*
0140 00000000 00076734 00000000 98CF7E20 00000000 388E2400 00000000 B92F87F0 *.....q.=.....g0*
0160 00000000 04418558 00000000 B92F97F0 00000000 1A3E5468 00000000 0000B8F0 *.....e.....p0.....0*
0180 00000000 0005F080 00000000 1A3E4F90 00000000 98D64AA2 00000000 B92F8940 *.....0.....|.....q0qs.....i *
```

Error Code: 0C4/AKEA Error Type: PROGRAM_CHECK Timestamp: C6BC0F99D77ACF04
Date (GMT) : 16/10/10 Time (GMT) : 00:04:46.267308
Date (LOCAL) : 15/10/10 Time (LOCAL) : 18:04:46.267308

KE_NUM: 0010 KE_TASK: 0F4EE700 TCA_ADDR: 00062700 DS_TASK: 0E5F5080

Program DFHRMDM was in control, but the PSW was elsewhere.
Error happened under the CICS RB.
CICS Registers and PSW.

PSW: 078D0000 B92F8A7A Instruction Length: 4 Interrupt Code: 10 Exception Address: 3D711000

Execution key at Program Check/Abend: 8
Space at Program Check/Abend: Basespace

[Branch Event Address: 00000000_392F8950](#)

64-BIT REGISTERS 0-15

```

0000 00000000 18E1EF30 00000000 1A3E5468 00000000 00007000 00000000 98D61FA8
0020 00000000 00076734 00000000 98CF7E20 00000000 388E2400 00000000 B92F87F0
0040 00000000 04418558 00000000 B92F97F0 00000000 1A3E5468 00000000 0000B8F0
0060 00000000 0005F080 00000000 1A3E4F90 00000000 98D64AA2 00000000 B92F8940
```

“CICS and then MVS Registers and PSW follow.”

Breaking Event Address Register (BEAR)

- Example using BEAR to diagnose a wild branch:

KERRD 1A3D69D0 KERNEL ERROR DATA

Error Code: 0C1/AKEA Error Type: PROGRAM_CHECK

Program DFHAPLI1 was in control, but the PSW was elsewhere.

CICS Registers and PSW.

PSW: 078D0000 00000002 Instruction Length: 2 Interrupt Code: 01 Exception Address: 000A0000

Execution key at Program Check/Abend: 8

Space at Program Check/Abend: Basespace

Branch Event Address: 00084A88

REGISTERS 0-15

0000	00000000	7FFFF000	7FFFF000	7FFFF000	7FFFF000	7FFFF000	7FFFF000	00000000
0020	00000000	7FFFF000	7FFFF000	00000000	00000000	00000000	00000000	00000000

00083250	00000000	00000000	5CC4C6C8	C5C9D740		*DFHEIP	
00083260	40000833	70F0F6F4	F0C91154	1011E4D2		0650I....UK	
00083270	F3F0F1F3	F3401400	C3C9C3E2	40F5F6F5		52360 ..CICS 565	
00083280	F560D4F1	F5404DC3	5D40C3D6	D7E8D9C9		5-M15 (C) COPYRI	
...							
00084A80	B20A3000	98ECD00C	0B0E58E0	C00C58EE		q.}....\{...	



Bear points to this Branch instruction.
Prior to the Branch is an instruction loading the above registers.

Kernel Stacks (KE)

- Kernel stacks show the sequence of CICS modules currently involved with a task.
- Kernels stacks contain register save areas and working storage for each CICS module.

KE_NUM	@STACK	LEN	TYPE	ADDRESS	LINK	REG	OFFSET	ERR	NAME
00B9	1EB5C020	0120	Bot	9D001C00	9D001FBC		0003BC		DFHKETA
00B9	1EB5C140	0320	Dom	9D01A660	9D01A878		000218		DFHDSKE
00B9	1EB5C460	0820	Dom	9D042C58	9D043E24		0011CC		DFHXMTA
00B9	1EB5CC80	05D0	Dom	9DB0B9C0	9DB0C97A		000FBA		DFHPGPG
			Int	+0002DC	9DB0BB52		000192		INITIAL_LINK
00B9	1EB5D250	0AD0	Dom	9DD0C700	800837A4		000000		DFHAPLI1
			Int	+002FD2	9DD0D1A4		000AA4		LE370_INTERFACE
			Int	+002DAC	9DD10764		004064		INVOKE_FOR_RECURSION
00B9	1EB5DD20	04A0	Sub	9DCE5000	9DCE6D66		001D66		DFHEIFC
			Int	+00141A	9DCE54D8		0004D8		CALL_FCFR
00B9	1EB5E1C0	0860	Dom	9E162200	9E16592A		00372A		DFHFCFR
			Int	+00B31A	9E163AE0		0018E0		IMPLICIT_OPEN
			Int	+0036EA	9E16D94A		00B74A		OPEN_FILE
00B9	0005F020	0A50	Sub	9E244200	9E24AF96		006D96		DFHFCFS
			Int	+00575E	9E245336		001136		OPEN_FILE
			Int	+006D60	9E249A82		005882		SETOPEN
00B9	00060020	0ED0	Sub	9E294100	9E29AE4A		006D4A		DFHFCR0
			Int	+000382	9E29434C		00024C		OPEN_FILE
			Int	+004554	9E294AB0		0009B0		PERFORM_VSAM_OPEN

Finding the z/OS TCB address (KE)

- Often we need to find the z/OS TCB for one of the CICS TCBS:
- **Verbx dfhpd700 'ke=3'**
- Use the selected KE_KTCB from the Kernel Task Summary.
- FIND the formatted KTCB control blocks.
- For the selected KTCB address, **KTCB+x'50'** contains the address of the z/OS TCB:

KTCB 0E3D5FF0 KTCB TABLE ENTRY

```
0000 D2E3C3C2 40404040 00000000 0E39EA98 0E39EA98 0E39F020 00000000 5166F0AE *KTCB      ..q...q..0.....0.*
0020 00000000 7D000000 00000000 00000000 80000001 00000000 06820000 D900D9D6 *....'.....b..R.R0*
0040 00000000 00000000 0E3D5FF0 40000000 008E5920 00000000 00006130 00000000 *.....^0 ...../.....*
```

- For one of the more common TCBS, like the QR, can also use the trace domain to quickly find the TCB address:
- **Verbx dfhpd700 'tr=2'** then enter **FIND QR**

```
AP 00E1 EIP EXIT SUSPEND OK          REQ(00F4) FIELD-A(00000000 ....) FIELD-B(00001208 ....)
TASK-00069 KE_NUM-0042 TCB-QR /008E55F8 RET-9061A2F2 TIME-18:04:46.2613956572
```

- In later releases the z/OS TCB is formatted in the summary:

KE_NUM	KE_TASK	STATUS	TCA_ADDR	TRAN_#	TRANSID	DS_TASK	KE_KTCB	ERROR	TCB	CURRENT_PSW
0001	1F6EC000	KTCB Step	00000000			00000000	1F730038		8FF1F8	078D1000_9F5707BC
0002	1F6EC630	KTCB QR	00000000			1F719F00	1F7331B8		8FC1C8	070C0000_811D4386
0003	1F6FB000	KTCB R0	00000000			1F728E00	1F732138		8FC3F8	078D1000_9F51864E
0004	1F6FB630	KTCB C0	00000000			1F728F00	1F826F80		8BDE88	078D1000_9F51864E
0005	1F70A000	KTCB F0	00000000			1F734F00	1F7310B8		8FC628	078D1000_9F51864E

Loader domain (LD)

- **Verbx dfhpd700 'ld=1'**

- Program Repertoire provides program length, use count etc.
- Program Storage Map provides a program's load point, entry point, PTF level (if applicable).

==LD: [PROGRAM REPERTOIRE](#)

PGM NAME	USE CNT	USERS	LOADS	COPIES	LENGTH	USE	TYP	ATTRB	EXEC KEY	R/A	MODE	DEFINITION DATE	TIME	CPE ADDRESS	PLIBE ADDRESS	STATUS
DFHERM	1	1	1	1	00005708	NUC	ANY	RSDNT	CICS	-	-	3/08/10	21:29:57	0E6AFAC0	0E652030	LOADED
DFHERMSP	2	2	1	1	00001600	NUC	ANY	RSDNT	CICS	-	31	3/08/10	21:29:58	0E6AFC60	0E652030	LOADED
DFHESC	1	1	1	1	00000668	NUC	ANY	RSDNT	CICS	-	-	3/08/10	21:29:57	0E6AFD30	0E652030	LOADED
...																
PROGRAM1	0	0	0	0	00000D20	APP	RPL	REUSE	USER	-	-	9/09/10	10:45:01	0F5F2370	0E652030	LOCATED
PROGRAM2	0	0	0	0	000019F0	APP	RPL	REUSE	USER	-	-	9/09/10	10:45:01	0F5F2440	0E652030	LOCATED
PROGRAM3	0	0	0	0	00002D50	APP	RPL	REUSE	USER	-	-	9/09/10	10:45:01	0F5F2510	0E652030	LOCATED

==LD: [PROGRAM STORAGE MAP](#)

PGM NAME	ENTRY PT	CSECT	LOAD PT.	REL.	PTF LVL	LAST COMPILED	COPY NO	USERS	LOCN	TYP	ATTRIBUTE	R/A	MODE	APE	ADDR
DFHAPXM	8008EF00	DFHAPXM	0008EF00	660	HCI6600	05/30/09 02.29	1	2	RDSA	ANY	RESIDENT	-	31	0E61C030	
		IPRAPXM	00090060												
DFHDLI	80090314	DFHDLI	00090200	0660	HCI6600	I 30/05 03.06	1	1	RDSA	ANY	RESIDENT	-	-	0E61C1F8	
		IPRDLI	000913E8												
DFHEITHG	00091620	-nohed-	00091600				1	1	RDSA	ANY	RESIDENT	-	-	0E61E030	
DFHERM	00098914	DFHERM	00098800	0660	UK48726	I 28/07 11.10	1	1	RDSA	ANY	RESIDENT	-	-	0E61F880	
		DFHERMS	0009CE28	0660	UK48726	I 28/07 11.10									
		DFHTIEM	0009D418	0660	HCI6600	I 30/05 05.09									

Program domain (PG)

- The Program domain has a Program Level control block (PLCB) that shows the sequence of application programs, TRUEs and GLUEs that are involved with a task.
- **Verbx dfhpd700 'pg=1'**
- FIND on the task number:

```
==PG: PTA SUMMARY FOR TRAN NUM : 44444, PTA ADDRESS : 153F56F0
LOG-LVL : 3          SYS-LVL : 0          TASK-LLE : 1655F160  PLCB : 16029268
=PG: TASK LLE SUMMARY
LLE-ADDR  PROGRAM      PPTE-ADD
1655F160   COBLPGM1     16666D98
1655F1F0   COBLPGM2     16427348
1655F5E0   COBLPGM3     1665ADF0

=PG: TASK PLCB SUMMARY
PROG DFHD2EX1 LVL 3  PLCB 16029268 LD 00000000 ENT 00000000 LEN 000000 PPTE 1622FD98 ENV TRUE INV PROGRAM2 EXIT
PROGRAM: DFHD2EX1 CPE: 162966B0 LIB: DFHRPL  CONCAT: 00

PROG PROGRAM2 LVL 2  PLCB 16171E68 LD 18AF8F10 ENT 98AF8F10 LEN 003370 PPTE 164A6AD8 ENV EXEC INV PROGRAM1 EXIT
COMMAREA 163A3878 LEN 77AA STORAGE U
PROGRAM: PROGRAM2 CPE: 16680C60 LIB: DFHRPL  CONCAT: 0E

PROG PROGRAM1 LVL 1  PLCB 1616F230 LD 18AFD000 ENT 98AFD13C LEN 0022B8 PPTE 16266C90 ENV EXEC INV CICS  EXIT
PROGRAM: PROGRAM1 CPE: 15383ED0 LIB: DFHRPL  CONCAT: 00
```

Program Level summary (PG)

- The LVL 1 program, PROGRAM1, is the initial program.
 - It's environment shows EXEC indicating a normal application program.
 - PROGRAM1 issues an EXEC CICS LINK to PROGRAM2.
- The LVL 2 program is PROGRAM2.
 - PROGRAM2 issues an SQL call.
- The LVL 3 program is DFHD2EX1, running as a Task Related User Exit (TRUE).
- PLCB summary is also useful for providing program name, length, and load point information.
- Note: Programs listed in the LLE Summary have been loaded on behalf of the current task. e.g. via COBOL call

LMQUEUE - Waiting on a lock

- **Verbx dfhpd700 'ds=1'**
- Dispatcher domain shows that tasks are in LMQUEUE suspends, indicating that tasks are waiting on a lock(s):

DS_TOKEN	KE_TASK	T	S	F	P	TT	RESOURCE TYPE	RESOURCE_NAME	W	TIME OF SUSPEND	TIMEOUT DUE	DTA (DSTSK)	AD	ATTACHER TOKEN	M	SUSPAREA	XM_TXN_TOKEN
...																	
0512813D	1E59C100	N	S	N	N	-		LMQUEUE	S	20:07:00.500	-	1D58FE00	XM	226FF300	QR	1D395470	226FF30000044071C
05806301	1E5FF900	N	S	N	N	-		LMQUEUE	S	20:16:02.558	-	1D590080	XM	22755100	QR	1D395620	2275510000044092C
0586B227	1E5B2900	N	S	N	N	-		LMQUEUE	S	20:58:22.757	-	1D590500	XM	2170D100	QR	1D582920	2170D10000044040C
058E7DA7	1E59C500	N	S	N	N	-		LMQUEUE	S	20:37:34.170	-	1D590B00	XM	22751700	QR	1D3958F0	2275170000044131C
0600E50B	1E52A100	N	S	N	N	-		LMQUEUE	S	20:58:10.436	-	1D5F2080	XM	21713D00	QR	1D582B60	21713D0000044039C
0604D7A5	1E56E100	N	S	N	N	-		LMQUEUE	S	20:09:01.663	-	1D5F2380	XM	226FFB00	QR	1D395500	226FFB0000044076C
060A2A1D	1E48E900	N	S	N	N	-		LMQUEUE	S	20:57:59.773	-	1D5F2800	XM	20EB9B00	QR	1D582800	20EB9B0000044034C
060C8D99	1E4A4500	N	S	N	N	-		LMQUEUE	S	20:05:26.882	-	1D5F2980	XM	226FC700	QR	1D3953B0	226FC70000044061C
060ED8AF	1E540900	N	S	N	N	-		LMQUEUE	S	20:18:03.300	-	1D5F2B00	XM	22755B00	QR	1D3956E0	22755B0000044101C
06824099	1E59C900	N	D									1D5F3200	XM	2173A700	QR		2173A70000044051C
0686199D	1E558900	N	S	N	N	-		LMQUEUE	S	20:00:47.058	-	1D5F3500	XM	2173A300	QR	1D395260	2173A30000044049C
07029D95	1E5F6500	N	D									1D5F4200	XM	20FCC300	QR		20FCC30000043505C
07046CFB	1E584900	N	R									1D5F4380	XM	1EDA6100	QR		1EDA610000043738C
07065887	1E4BA100	N	S	N	N	-		LMQUEUE	S	20:00:30.503	-	1D5F4500	XM	2170DD00	QR	1D395200	2170DD0000044047C
070C338D	1E48E100	N	D									1D5F4980	XM	2170DB00	QR		2170DB0000044046C
07040001	15D92500	N	S	P	N	-	ENQUEUE	FCDSRECD	S	20:01:11.363	-	2B0E2380	XM	2E40C030	QR	2B0E2380	2E40C03000043203C
070EFAFF	1E584100	N	S	N	N	-		LMQUEUE	S	20:59:32.626	-	1D5F4B00	XM	2170D900	QR	1D3951A0	2170D90000044044C
0710FCDF	1E4E6100	N	S	N	N	-		LMQUEUE	S	20:05:07.555	-	1D5F4C80	XM	226FC300	QR	1D395350	226FC30000044059C
07126B47	1E540100	N	S	N	N	-		LMQUEUE	S	20:06:13.407	-	1D5F4E00	XM	226FCB00	QR	1D395410	226FCB0000044065C
0782000B	1E5DE900	N	S	N	N	-	EKCWAIT	SINGLE	W	05:08:26.187	-	1D5F6200	XM	1D609B00	QR	00006058	1D609B0000000076C
07840007	1E5FF500	N	S	P	N	-			M	05:08:25.530	-	1D5F6380	XM	1D60A100	QR	1E62C33C	1D60A10000000053C
07860005	1E5FE900	N	S	P	N	-			M	18:24:57.263	-	1D5F6500	XM	1D60AB00	QR	1E61E33C	1D60AB0000000054C
07880003	1E5FE500	N	S	N	N	-		LMQUEUE	S	20:04:02.187	-	1D5F6680	XM	1E941100	QR	1D395290	1E94110000044055C
...																	

Lock Manager (LM)

- **Verbx dfhpd700 'lm=1'**
- FIND on keyword 'wait' to find the Lock Wait Queue and see what lock(s) tasks are waiting for:

==LM: LOCK WAIT QUEUE

LOCK NAME	ADDRESS	-> NEXT	OWNER	MODE	SUSPEND TOKEN	STATUS
----	-----	-----	-----	----	-----	-----
DUDATSET	15B991E4	15B99234	16E67100	EXCL	00930003	
<u>TSLOCK</u>	1D5BDE04	1D5BDDF0	1E59C500	EXCL	015B0001	
	1D5BDDF0	1D5BDDDC	1E4FC500	EXCL	01590001	
	1D5BDDDC	1D5BDDC8	1E4E6900	EXCL	01570001	
	1D5BDDC8	1D5BDDDB4	1E5C8500	EXCL	01550001	
	1D5BDDDB4	1D5BDDA0	1E5B2100	EXCL	01530001	

Lock Manager (LM)

- FIND on the lock name PREV to see the Allocated Locks summary and determine what task currently owns the lock
- The address listed as the lock owner identifies a Kernel TAS control block address.

==LM: ALLOCATED LOCKS

LOCK NAME	LOCK TOKEN	<u>OWNER</u>	MODE	COUNT	# LOCK REQUESTS	# LOCK SUSPENDS	-> QUEUE
----	-----	-----	----	-----	-----	-----	-----
DUDATSET	15530020	16DDF900	EXCL		181	80	15B991E4
...							
<u>TSLOCK</u>	34603DD0	<u>15D92500</u>	EXCL		327477	3648517	1D5BDE04

Identify the Lock Owner

- Format the Kernel summary and FIND on the TAS address to identify the owning task.
- **Verbx dfhpd700 'ke=1'**
- Format the Dispatcher summary and find the task (using the TAS address or the Task #), and see what the lock owner is waiting for.
- **Verbx dfhpd700 'ds=1'** (some fields deleted)

KE_NUM	KE_TASK	STATUS	TCA_ADDR	TRAN_#	TRANSID	DS_TASK	KE_KTCB	ERROR
0038	15D92500	Not Running	150DA700	42303	BIGD	344DB680	35668FF8	

KE_TASK	T	S	F	P	TT	RESOURCE TYPE	RESOURCE_NAME	TIME OF SUSPEND	TIMEOUT DUE	DTA (DSTSK)	M	SUSPAREA	XM_TXN_TOKEN
15D92500	N	S	P	N	-	ENQUEUE	FCDSRECD	18:41:51.98	-	22128B00	QR	22128B00	2071E70000 42303 C

Enqueue Domain (NQ)

- If Dispatcher summary shows a task waiting on an **ENQUEUE:**

KE_TASK	T	S	F	P	TT	RESOURCE TYPE	RESOURCE_NAME	TIME OF SUSPEND	TIMEOUT DUE	DTA (DSTSK)	M	SUSPAREA	XM_TXN_TOKEN
15D92500	N	S	P	N	-	ENQUEUE	FCDSRECD	18:41:51.988	-	22128B00	QR	22128B00	2071E700042303C

- **Verbx dfhpd700 'nq=1'**
- **FIND on the ENQUEUE name/type.** e.g. FCDSRECD

==NQ: ENQUEUE POOL SUMMARY - [FCDSRECD](#)

Default shunt action:	Retain
*Total enqueue requests:	2345
*Total requests that have waited:	65
*Total requests failed busy:	47
*Total requests failed locked:	0
*Total requests timed out:	0
*Total enqueues that were retained:	0

*NOTE: These values were reset at 04:57:03 (last statistics interval collection)

ENQUEUE Summary FCDSRECD (NQ)

- FIND on your task#. Task # 42303 is waiting on a file record lock owned by a KRUD task, # 42046:
- For an ENQUEUE type FCDSRECD, the first word of the ENQUEUE name (x'10B70440') is the address of the Dataset Name Block, followed by the key of the record (or a portion of the key. Entire key can be found in the NQEA).
 - A resource name of **FCDSRECD** indicates a wait for a record lock in a VSAM file or **CICS**-maintained data table

				NQEA	Tran	OWNER / WAITER	Lifetime	Hash	
Enqueue Name	Len	Sta	Address	id	Num	Local Uowid	Uow Tsk	Indx	
X'10B70440'	100000000000000000000000	26	Act	0FB7EE40	KRUD	42046 BB66EA4300225621	1 0	10	
X'F1F0F0F0F0F0F0F0F0F0F0									
				Waiter :	0FB7ED80 CSMI	46047 BB66EA431739D1A1	1 0	10	
				Waiter :	13CA8480 TTFN	42545 C3F038A5953D5204	1 0	47	
				Waiter :	13CA5900 BIGD	42303 C3F038B4CEE9D404	1 0	47	
X'10B70440'	CCCCCCCCCCCCCCCCCCCCCC	26	Act	13CA5C00	BIGD	42303 C3F036ABB02D8E06	2 0	47	
X'C3C3C3C3C3C3C3C3C3C3									
				Waiter :	13CA2D80 TTFN	51124 C3F03700BC9BB046	1 0	47	
				Waiter :	1234D380 R0FL	51793 C3F0371F52060486	1 0	47	

File Control component (FCP)

- **Verbx dfhpd700 'fcp=1'**
- Find on the dataset name block address found in the NQ domain to identify the CICS file associated with the ENQUEUE request..

ADDRESS	FILENAME	ACC	TYPE	MODE	RLS	LSR	REM	SLG	SREQS	STATUS	JID	DSNB-OBJ	DSNB-BAS	FR
10B79B28	<u>BIGG</u>		VSAM KSDS	BASE NO	1	NO	YES	RUADB	OPEN	ENA	0	10B70440	<u>10B70440</u>	YES

Application domain (AP)

- The Application domain can be formatted with:
 - **Verbx dfhpd700 'ap=3'**
- All task storage acquired on behalf of a task is formatted.
 - Any storage violations currently detected by CICS are flagged when the leading and trailing storage accounting areas don't match.
- Task-related control blocks including the Task Control Area (TCA), and EXEC CICS request areas are formatted.
 - EXEC Interface Block (EIB) and EXEC Interface User Structure (EIUS) can be used to find the most recent EXEC CICS request for a task, and identify the program that made the request.
- Can selectively format storage associated with a single task:
 - **Verbx dfhpd700 'aps=<taskid=xxxxx>**
 - If available, will also format LE/370 storage information for the task using the LE VERBEXIT CEEERRIP.

Application domain (AP)

- **Verbx dfhpd700 'ap=3'**

- FIND on keyword 'violation' to see any storage violations currently detected by CICS for all task storage.
- The beginning of this storage should have a check zone, U0019984, matching the trailer which is intact.

USER31.19984 1E317490 USER storage above 16MB

```
0000  40404040 40404040 40404040 40404040  40404040 0000000C 0000000C 0000000C * .....*
0020  00000000 0C000000 0C000000 0C000000  0C000000 0C00000C 0000000C 00000C00 * .....*
0040  00000000 0C00000C 00000C00 000C4040  40404040 40404040 40404040 40404040 * .....*
0060  40404040 40404000 00000C00 00000C00  00000C00 00000C00 000C0000 0C00000C * .....*
0080  00000C00 00000C40 40404040 40404040  40404040 40404040 40404040 40404040 * .....*
00A0  40404040 40000000 0C000000 0C000000  0C000000 000C0000 000C0000 000C0000 * .....*
00C0  000C0000 000C0000 0C000000 0C00000C  00000000 000C0000 0C00000C 00000C40 * .....*
00E0  40404040 40404040 40404040 40404040  40404040 40404040 0000000C 0000000C * .....*
0100  0000000C 0000000C 00000C00 000C0000  0C00000C 0000000C 40404040 40404040 * .....*
0120  40404040 40404040 40404040 40404040  40404040 40400000 000C0000 000C0000 * .....*
0140  000C0000 00000C00 00000C00 00000C00  00000C00 00000C00 000C0000 000C0000 * .....48
```


Find the most recent EXEC CICS request (AP)

- **Verbx dfhpd700 'aps=<taskid=xxxxx>**
- Page forward to find the System EIB, EIUS, User EIB.
- The System Exec Interface Block (EIB) +x'1B' (2 bytes) contains the function code for the most recent EXEC CICS request. e.g. **0602**

SYSEIB.44444 0005A494 System EXEC Interface Block

```
-0008                                     5CE2E8E2 C5C9C240 *                               *SYSEIB *
0000 0141919C 0110130F C2C9C7C4 0044444C C1D6D9F1 000002D5 00807C06 02000000 *..j....BIGD....AOR1...N..@....*
0020 00000000 00000000 00000000 00000000 00000040 40404040 40404000 00000000 *.....*
0040 00000000 00000000 00000000 00000000 00000000 00                                *.....*
```

EIUS.44444 00102008 EXEC Interface User Structure

```
0000 00B46EC4 C6C8C5C9 E4E24040 40404040 17E00008 00000000 17E03950 00000000 *..>DFHEIUS      .\.....\.&....*
0020 00000000 00000000 00000000 00000000 00000000 00000000 00000000 00000000 *.....*
0040 00000000 00000000 001020D0 17E03878 00102418 00000000 00000000 00000000 *.....}. \.....*
...
```

EIB.44444 001020D0 EXEC Interface Block

```
-0010                                     00656EC4 C6C8C1D7 6DC4C6C8 C5C9C25C *                               ..>DFHAP_DFHEIB**
0000 0141919C 0110130F C2C9C7C4 0044444C C1D6D9F1 000002D5 00807C06 04000000 *..j....BIGD....AOR1...N..@....*
0020 00000000 00000000 00000000 00000000 00000040 40404040 40404000 00000000 *.....*
0040 00000000 00000000 00000000 00000000 00000000 00                                *.....*
```

The most recent EXEC CICS request (AP)

- The description of the EIB function codes (field EIBFN) can be found searching in the CICS Knowledge Center (or CICS Application Programming Reference manual).
 - Search on keyword EIBFN and the 2-byte code:

Code	Command
-------------	----------------

0602	READ
-------------	-------------

0604	WRITE
-------------	--------------

- If the EIB function code in the (User) EIB is different than the function code in the System EIB, then typically the current EXEC CICS request has not yet completed.
 - The function code in the System EIB is the most current request.
 - The current EXEC CICS request in the example is an EXEC CICS READ FILE. The previous request was a WRITE FILE.

Who issued the last EXEC CICS request ?

- **Verbx dfhpd700 'aps=<taskid=xxxxx>'**
- FIND the EIUS. **EIUS +x'50'** contains the address of the Register Save Area (RSA) for the program issuing the EXEC CICS request.

EIUS.44444 00102008 EXEC Interface User Structure

```
0000 00B46EC4 C6C8C5C9 E4E24040 40404040 17E00008 00000000 17E03950 00000000 *..>DFHEIUS      .\.....\.&....*
0020 00000000 00000000 00000000 00000000 00000000 00000000 00000000 00000000 *.....*
0040 - Note: Field name is EIUS_RSA_ADDR. 00000000 00000000 00102416 00000000 00000000 00000000 *.....}. \.....*
```

- The registers are saved in the RSA at offset x'C' in the order Reg14 - Reg12. These will be the application's registers at time of the EXEC CICS request.

- Reg14 will point into the requesting program, immediately after the EXEC CICS request.

```
RSA:
00102418          00000000 17E0B828 | ..... \.. |
00102420 00000000 15F1DAC0 00000000 17E1068C | ..... 1. { ..... |
00102430 18A46060 97E0C0D8 18910DA0 17E10618 | .u--p\{Q.j ..... |
00102440 189109A8 189109E8 17936440 17F01680 | .j.v.j.Y.l. 0. |
00102450 17E0BA28 001020D0 17F0EA38 15F1D928 | .\.....}. 0...1R. |
```

- Identify the requesting module using the Loader domain, the Program domain, or backing up in storage looking for a module ID.

TK – Task Summary

- **Verbx dfhpd700 ‘TK’**

- Provides you a ‘One stop shop” to get pertinent information for a task
 - Contains some of the same information from various different domains all in one place

==TK: TASK SUMMARY TABLE

W = Waiting for first dispatch Y=Yes N=No
 F = Flagged for Abend Y=Yes N=No
 S = Current state D=DISPATCHABLE S=SUSPENDED R=RUNNING A=RUNNING ABTERM YES J=RUNNING IN JVM E=RESUMED
 SC = Start Code

Tran num	Tran id	Term ID	SC	Primary Client	W	Start Time (LOCAL)	Time entered Current state	Elapsed Time	Total CPU Time	Current TCB	S	Resource Type	Resource Name	F
00004	CMPE	N/A	C	None	N	00:32:19.330	00:32:19.337	004:16:07:47.495	00:00.000255	L8001	S	MPDQEMW	MPSUSPND	N
00005	CEPM	N/A	C	None	N	00:32:19.353	00:32:19.354	004:16:07:47.473	00:00.000092	EP000	S	EPECQEMT	EPSUSPND	N
00006	CSOL	N/A	C	None	N	00:32:19.356	16:40:05.757	004:16:07:47.470	20:27.217126	SL	R			N
00007	CSSY	N/A	C	None	N	00:32:19.547	00:00:00.015	004:16:07:47.279	00:00.004682	QR	S	ICMIDNTE	DFHAPTIM	N
00008	CSSY	N/A	C	None	N	00:32:19.547	16:40:04.912	004:16:07:47.279	00:01.389083	QR	S	ICEXPIRY	DFHAPTIX	N
00011	CSTP	N/A	C	None	N	00:32:21.974	16:40:04.912	004:16:07:44.852	00:04.292483	QR	S	TCP_NORM	DFHZDSP	N
00025	CEPF	N/A	C	None	N	00:32:22.586	00:32:22.586	004:16:07:44.240	00:00.000119	EP001	S	ECDQEMW	ECSUSPND	N
00026	CFQS	N/A	C	None	N	00:32:22.588	16:38:00.614	004:16:07:44.238	00:00.003827	QR	S	FCCFQS		N
00027	CFQR	N/A	C	None	N	00:32:22.588	23:55:02.529	004:16:07:44.238	00:00.000151	QR	S	FCCFQR		N
00028	CSNC	N/A	C	None	N	00:32:28.154	15:32:20.182	004:16:07:38.671	00:00.575566	QR	S	CSNC	MROQUEUE	N
00131	CONL	N/A	C	None	N	00:32:36.684	13:20:49.907	004:16:07:30.142	00:00.072575	QR	S			N
00132	CSSY	N/A	C	None	N	00:32:38.506	00:32:38.507	004:16:07:28.320	00:00.000152	QR	S	KCCOMPAT	SINGLE	N
00133	COIO	N/A	C	None	N	00:32:38.638	16:39:54.881	004:16:07:28.187	00:02.950461	QR	S	USERWAIT	WorkWait	N

Trace (TR)

•Verbx dfhpd700 'tr=1'

-Formats abbreviated CICS trace entries.

•Verbx dfhpd700 'tr=2'

-Formats full CICS trace entries. Time is Local time.

•Verbx dfhpd700 'tr=3'

-Formats abbreviated trace entries followed by full trace entries.

Trace sequence number



```

51392 QR  AP 00E1 EIP  ENTRY READ                                0004,1EA3C158 .tA.,09000602 .... =000050=
51392 QR  AP 04E0 FCFR  ENTRY READ_SET                        FILE1 ,00000000,9EA41D63,NO,EQUAL,FCT_VALUE,KEY,NO,NO      =000051=
51392 QR  DD 0301 DDLO  ENTRY LOCATE                        1E95D820,1E5E0E91,CALLER,FCT,FILE1                        =000052=
51392 QR  DD 0302 DDLO  EXIT  LOCATE/OK                     00000000 , 1EC715B8                                         =000053=
51392 QR  AP 04E1 FCFR  EXIT  READ_SET/EXCEPTION            FILE_DISABLED,0,00000000,0,00000000,,,NO                      =000054=
51392 QR  AP 00E1 EIP  EXIT  READ                          DISABLED                                00F4,00000032 .....,00540602 .... =000055=
  
```

AP 00E1 EIP ENTRY READ REQ(0004) FIELD-A(1EA3C158 .tA.) FIELD-B(09000602)

TASK-51392 KE_NUM-0080 TCB-QR /009BD690 RET-A09322AC TIME-01:37:38.4093793127 INTERVAL-00.0000032500 =000050=

AP 04E0 FCFR ENTRY - FCN(READ_SET) FILE_NAME(FILE1) ENVIRONMENT_IDENTIFIER(00000000) RECORD_ID_ADDRESS(9EA41D63) GENERIC(NO)
KEY_COMPARISON(EQUAL) READ_INTEGRITY(FCT_VALUE) RECORD_ID_TYPE(KEY) CONDITIONAL(NO) BYPASS_SECURITY_CHECK(NO)

```

TASK-51392 KE_NUM-0080 TCB-QR /009BD690 RET-9D9FE692 TIME-01:37:38.4093797189 INTERVAL-00.0000004062 =000051=
1-0000 00880000 00000038 00000000 00000000 B40BC12C 7C800000 02000100 00000000 *.h.....A.@.....
0020 00000000 C6D0D3C5 F1404040 00000000 00000000 00000000 00000000 *....FILE1 .....
0040 00000000 00000000 00000000 00000000 00000000 00000000 9EA41D63 00000000 *......u.....
0060 00000000 00000000 00000000 00000000 00000000 00000000 00000202 01000002 01020002 *......
0080 00000200 00000000                                     *.....
  
```

Short trace entries & Exception entries (TR)

- **Verbx dfhpd700 'trs=<short>'**
- Short trace entries contain the same information as the abbreviated trace entries plus the following information from the full trace entries:
 - Interpreted parameter list, showing keyword and value.
 - Return address
 - Time stamp / Interval
- CICS writes Exception trace entries for most errors and abnormal conditions. These exception entries cannot be suppressed, and are written even if CICS tracing is stopped.
 - FIND on ***EXC** to see them:

```
41394 QR AP 00E1 EIP ENTRY READ                                REQ(0004) FIELD-A(1EA3C158 .tA.) FIELD-B(09000602 ....)
                                                                RET-A09322AC 01:37:38.4093793127 00.0000032500 =000050=
41394 QR AP 04E0 FCFR FCN(READ_SET) FILE_NAME(FILE1) ENVIRONMENT_IDENTIFIER(00000000) RECORD_ID_ADDRESS(9EA41D63) GENERIC(NO)
                                                                KEY_COMPARISON(EQUAL) READ_INTEGRITY(FCT_VALUE) RECORD_ID_TYPE(KEY) CONDITIONAL(NO) BYPASS_SECURITY_CHECK(NO)
                                                                RET-A09322AC 01:37:38.4093793127 00.0000032500 =000051=
```

```
53069 QR AP 1942 APLI *EXC* Program-Check START_PROGRAM,PROGRAM1,CEDF,FULLAPI,EXEC,NO,00000000 =000066=
```

Formatting selected tasks and entries

- Verbx dfhpd700 'trs=<taskid=xxxxx,abbrev|full|short>'
 - Formats trace entries for the selected task only.
 - e.g. **verbx dfhpd700 'trs=<taskid=12345,full>'**
 - Can select multiple tasks:
 - e.g. **verbx dfhpd700 'trs=<taskid=(xxxxx,yyyyy),abbrev>'**
- Verbx dfhpd700 'trs=<entry_num=(nnnnnnn-nnnnnn)>'
 - Formats trace entries selected by trace sequence numbers.
 - If you encounter message DFHPD0123 for an error/program check during trace formatting, trace formatting stops. You can format the remaining trace entries if you bypass the failing one:
 - e.g. **verbx dfhpd700 'trs=<entry_num=xxxxxx-999999,full>'**
 - where xxxxxx is the last 'good' trace entry +2 to get around the entry in error.

Additional trace options

- 'trs=<ke_num=(nnnn,nnnn)>'
 - List entries for a specific Kernel number(s).
- 'trs=<termid=tttt>'
 - List entries pertaining to a specific Terminal ID.
- 'trs=<timerg=(hhmmss-hhmmss)>'
 - List entries from a specific time range.
- 'trs=<tranid=tran>'
 - List all trace records related to a transaction ID.
- Note: The full list of additional trace options can be found in the CICS Knowledge Center – see Trace Selection Parameters

Summary

- Some basic IPCS commands
- CICS Verbexit DFHPDxxx
- Questions?